

Cable Kit 3166 Interface 3130 or 3009/09

Mimer SoftRadio for Icom IC-A110 & IC-A120



Remote functionality

This cable kit will together with the Mimer Network Interface LE give remote control of the radios audio and PTT functions.



Channel change is not possible.

Radio programming

No special programming is needed in the radio.

A110: The volume control shall be set for “five clicks down” from max.

A120: The volume control knob shall be set for 50% volume. This is when the knob points straight up (12 o’clock).

Cable Kit

The red and black wires shall be connected to 12VDC, red is positive.

We strongly recommend that a separate power supply is used for the network interface, apart from the power supply of the radio.

This is called for by the radio being very sensitive on the microphone line, the AGC picks up every small disturbance.

The network interface consumes max 0,3A.



Cable Kit Icom IC-A110 & IC-A120